

□□□□□□□□□□ - □□□□□□□□

□□	
□□□	□□□□□□
□□□□□	Amlogic S905X3 □□ ARM Cortex-A55 □□ 2.0GHz
□□□□□	ARM Mali-G31
□□	16GB/32GB EMMC
□□	2GB/4GB DDR4
□□□□□□	□□9.0/ATV
□□	4.1 □□□
□□□□□□	Widevine□Verimatrix/ Playready □□□
4G LTE □□□□□□	
□□4G LTE□□□□□□	LTE-FDD/LTE-TDD/WCDMA/TD-SCDMA/EDGE/GPRS/GSM□□□150Mbps□□ □50Mbps
MHZ-E□□□□	B1/B3/B5/B7/B8/B20@FDD LTE□ B1/B5/B8@WCDMA□850/900/1800/1900@GSM
MHZ-A□□□□	B2/B4/B8/B17@FDD LTE□ B38/B39/B40/B41@TDD LTE□B1/B8@WCDMA□B34/39@TD-SCDMA□900/1800@GSM
MHZ-CE□□□/□□/□□□□□□	B1/B3/B5/B8@FDD LTE□B38/B39/B40/B41@TDD LTE□B1/B8@WCDMA□B34/B39@TD-SCDMA□BC0@CDMA2000 1X/EXDO□ 900/1800@GSM
MHZ-E□□□□□□□□□□/□□/□□/□□□	B1/B3/B5/B7/B8/B20@FDD LTE□B38/B40/B41@TDD LTE□ B1/B5/B8@WCDMA□ B3/B8@GSM
MHZ-V(□□)	B4/B13@FDD LTE
MHZ-A(□□)	B2/B4/B12@FDD LTE□ B2/B4/B5@WCDMA
MHZ-AU(□□□□/□□□□/□□)	B1/B2/B3/B4/B5/B6/B7/B8/B28@FDD LTE□ B40@TDD LTE□ B1/B2/B5/B8@WCDMA□ B2/B3/B5/B8@GSM
MHZ-J(□□)	B1/B3/B8/B18/B19/B26@FDD LTE□ B41@TDD LTE□ B1/B6/B8/B19@WCDMA
□□□□□□□□	
□□&□□	VP9/H.265/AVS2 □□ 4Kx2K@60fps□H.264 4K @30fps□AVS/VC-1/MPEG1-4 1080P @60fps H.264/H.265 1080P @60fps □□MPEG1/2/4□H.265/HEVC□AVS2□□ □AVC/VC-1□RM/RMVB□Xvid/DivX3/4/5/6□RealVideo8/9/10 Avi/Rm/RmVb/Ts/Vob/Mkv/Mov/ISO/wmv/asf/flv/dat/mpg/mpeg MP3/WMA/AAC/WAV/OGG/DDP/TrueHD/HD/FLAC/APE □□ JPEG/BMP/GIF/PNG/TIFF
□□□□□	HDR 10□□□□□
□□/□□	
HDMI	HDMI 2.1 □□ 3D□HDR□CEC □ 4Kx2K@60fps □□□□□
□□□□□	□□
USB	1*USB 2.0, 1*USB 3.0 □□ USB □□□□□□ USB □□□
RJ45	10/100M□□RJ-45□□□□
□□□□	Miracast□DLNA□Airplay□Skype□Netflix□Twitter□Picasa□Youtube□Flicker□ Facebook□□□□□□□□□□
□□□	WiFi 11ac□□ 4.1 IEEE802.11 a/b/g/n/ac(AP6255) 4G/5G
TF□	□□
SPDIF	□□□□□□□
□□□□	□□□□□□□□□□
LED□□□□	□□□□□□□□□□□□
LED□□□□□	1* LED□□□□□□□□□□RTCS□□□□USB□□
□□□	

